arXiv:1702.04171v1 [math.CA] 14 Feb 2017

JACOB'S LADDERS, NONLINEAR INTERACTIONS BETWEEN ζ-OSCILLATING SYSTEMS AND CORRESPONDING CONSTRAINTS

JAN MOSER

Abstract. In this paper we introduce new class of nonlinear interactions of ζ-oscillating systems. The main formula is generated by corresponding subset of the set of trigonometric functions. Next, the main formula generates certain set of two-parts forms. For this set the following holds true: the cube of two-part form is asymptotically equal to other two-part form – short functional algebra.

1. Introduction

1.1. Let us remind that we have obtained in our paper [8] certain class of formulae linear in different variables of the following type

$$\prod_{r=1}^{k}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r\right)}{\zeta\left(\frac{1}{2}+i\beta_r\right)}\right|^2,\ k=1,\dots,k_0, \tag{1.1}$$

i.e. linear in different oscillating systems. Namely, see formulae in [8]:

$$(7.1),\ (7.3),\ (7.4),\ (8.2),\ (8.4),\ (8.5). \tag{1.2}$$

It is, for example, the formula (7.1):

$$\begin{aligned}&\cos^2(\alpha_0^{2,2})\prod_{r=1}^{k_2}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{2,2}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{2}\right)}\right|^2+\\&+\sin^2(\alpha_0^{1,1})\prod_{r=1}^{k_1}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{1,1}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{1}\right)}\right|^2\sim 1,\\&L\to\infty,\ 1\le k_1,k_2\le k_0,\ L,k_0\in\mathbb{N},\end{aligned} \tag{1.3}$$

where

$$\begin{aligned}&\alpha_0^{1,1}=\alpha_0^1(U,\mu,L,k_1;\sin^2 t),\dots\\&\beta_r^1=\beta_r(U,\mu,L,k_1),\\&\alpha_0^{2,2}=\alpha_0^2(U,\mu,L,k_2;\cos^2 t),\dots\\&\beta_r^2=\beta_r(U,\mu,L,k_2).\end{aligned}$$

Remark 1. We have called the formula (1.2) as the ζ-analogue of the elementary trigonometric identity

$$\cos^2 t+\sin^2 t=1.$$

Key words and phrases. Riemann zeta-function.

Next, we have introduced in our paper [8] the following notions in connection with the formula (1.2):

(a) functionally depending ζ-oscillating systems and linearly connected ζ-oscillating systems, (see [8], beginning of section 2.4),
(b) interaction between corresponding ζ-oscillating systems (see [8], Definition 4).

Remark 2. By (a) and (b) we may assume in the context of the paper [8] the following:

$$\text{interaction} \;=\; \text{linear interaction},$$

(see, for example, (1.3), comp. [9], Remark 1).

Remark 3. Moreover, we notice that the ζ-oscillating system itself (comp. (1.1)) is a complicated nonlinear system (comp. [8], (1.7), i.e. the spectral form of the Riemann-Siegel formula).

1.2. Next, let us remind the following notions we have introduced (see [1] – [7]) within the theory of the Riemann zeta-function:

(A) Jacob's ladders, (see [1], comp. [2]),
(B) ζ-oscillating system, (see [7], (1.1)),
(C) factorization formula, (see [5], (4.3) – (4.18), comp. [7], (2.1) – (2.7)),
(D) metamorphosis of the ζ-oscillating systems:
  (a) first, the notion of metamorphoses of an oscillating multiform [4],
  (b) after that, the notion of metamorphoses of a quotient of two oscillating multiform, [5],
(E) $\mathcal{Z}_{\zeta,Q^2}$-transformation (or device), [7].

1.3. In this paper, we shall present certain class of nonlinear interaction formulae, namely:

(a) containing nonlinearities in variables of kind (1.1), (comp. Remark 2),
(b) describing interaction between corresponding ζ-oscillating systems, i.e. every of these is functionally depending upon others of these ζ-oscillating systems.

The main result is expressed by the following nonlinear formula:

$$\begin{aligned}
&\prod_{r=1}^{k_1}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{1,k_1}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_1}\right)}\right|^2 \sim \\
&\sim \frac{\cos(\alpha_0^{2,k_2})}{\cos^3(\alpha_0^{1,k_1})}\prod_{r=1}^{k_2}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{2,k_2}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_2}\right)}\right|^2 - \\
&-\frac{U^2}{3}\frac{1}{\cos^3(\alpha_0^{1,k_1})\cos^3 U}\times \\
&\times\left\{\cos^2(\alpha_0^{3,k_3})\prod_{r=1}^{k_3}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{3,k_3}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_3}\right)}\right|^2 - \sin^2(\alpha_0^{4,k_4})\prod_{r=1}^{k_4}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{4,k_4}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_4}\right)}\right|^2\right\}^3, \\
&L\to\infty,\ 1\le k_1,k_2,k_3,k_4\le k_0,
\end{aligned} \tag{1.4}$$

(comp. (1.3), (1.4) and (a) in the beginning of this section).

2. LEMMAS

2.1. Since

$$\int \cos^3 t\mathrm{d}t = \sin t - \frac{1}{3}\sin^3 t,$$

then

$$\int_{2\pi L}^{2\pi L+U} \cos^3 t\mathrm{d}t = \sin U - \frac{1}{3}\sin^3 U,\ L \in \mathbb{N},$$

and

$$\frac{1}{U}\int_{2\pi L}^{2\pi L+U} \cos^3 t\mathrm{d}t = \frac{\sin U}{U} - \frac{U^2}{3}\left(\frac{\sin U}{U}\right)^3.$$

Of course,

$$f_1(t) = \cos^3 t \in \tilde{C}_0[2\pi L, 2\pi L + U], \tag{2.1}$$

(the class of functions $\tilde{C}_0$ has been defined in our paper [9]), where

$$t \in [2\pi L, 2\pi L + U],\ U \in \left(0, \frac{\pi}{2} - \epsilon\right],$$

and $\epsilon > 0$ is sufficiently small. Consequently, we obtain for generating of the factorization formula by making use our algorithm (see [8], (3.1) – (3.11)) the following

Lemma 1. For the function (2.1) there are vector-valued functions

$$(\alpha_0^{1,k_1}, \alpha_1^{1,k_1}, \dots, \alpha_{k_1}^{1,k_1}, \beta_1^{k_1}, \dots, \beta_{k_1}^{k_1}),\ k_1 = 1, \dots, k_0,\ k_0 \in \mathbb{N}$$

(k_0 is arbitrary and fixed) such that the following factorization formula holds true:

$$\begin{aligned} &\prod_{r=1}^{k_1}\left|\frac{\zeta\left(\frac{1}{2} + i\alpha_r^{1,k_1}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^{k_1}\right)}\right|^2 \sim \\ &\sim \left[\frac{\sin U}{U} - \frac{U^2}{3}\left(\frac{\sin U}{U}\right)^3\right]\frac{1}{\cos^3(\alpha_0^{1,k_1})},\ L \to \infty, \end{aligned} \tag{2.2}$$

where

$$\begin{aligned} &\alpha_r^{1,k_1} = \alpha_r(U, L, k_1; f_1),\ r = 0, 1, \dots, k_1, \\ &\beta_r^{k_1} = \beta_r(U, L, k_1),\ r = 1, \dots, k_1, \\ &2\pi L < \alpha_0^{1,k_1} < 2\pi L + U\ \Rightarrow\ 0 < \alpha_0^{1,k_1} - 2\pi L < U, \\ &1 \le k_1 \le k_0. \end{aligned} \tag{2.3}$$

Remark 4. In the asymptotic formula (2.2) the symbol $\sim$ stands for (see [8], (3.8))

$$= \left\{1 + \mathcal{O}\left(\frac{\ln\ln L}{\ln L}\right)\right\}.$$

2.2. Let

$$f_2(t) = \cos t,\ t \in [2\pi L, 2\pi L + U],\ U \in \left(0, \frac{\pi}{2} - \epsilon\right]. \tag{2.4}$$

Since

$$f_2(t) \in \tilde{C}_0[2\pi L, 2\pi L + U]$$

then we obtain by similar way as in the case of Lemma 1 the following.

Lemma 2. For the function (2.4) there are vector-valued functions

$$(\alpha_0^{2,k_2}, \alpha_1^{2,k_2}, \dots, \alpha_{k_2}^{2,k_2}, \beta_1^{k_2}, \dots, \beta_{k_2}^{k_2}),\ k_2 = 1, \dots, k_0,\ k_0 \in \mathbb{N}$$

(k_0 is arbitrary and fixed) such that the following factorization formula holds true:

$$\prod_{r=1}^{k_2} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{2,k_2}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^{k_2}\right)} \right|^2 \sim \frac{\sin U}{U} \frac{1}{\cos(\alpha_0^{2,k_2})},\ L \to \infty, \tag{2.5}$$

where

$$\begin{aligned} &\alpha_r^{2,k_2} = \alpha_r(U, L, k_2; f_2),\ r = 0, 1, \dots, k_2, \\ &\beta_r^{k_2} = \beta_r(U, L, k_2),\ r = 1, \dots, k_2, \\ &0 < \alpha_0^{2,k_2} - 2\pi L < U, \\ &1 \le k_2 \le k_0. \end{aligned} \tag{2.6}$$

2.3. Next, let us remind (see [8], (8.1) and also (4.2), (4.3), (4.6), (4.7)) the following formula

$$\begin{aligned} &\frac{\cos^2(\alpha_0^{2,2})}{\cos(2\mu + U)} \prod_{r=1}^{k_2} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{2,2}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^2\right)} \right|^2 - \frac{\sin^2(\alpha_0^{1,1})}{\cos(2\mu + U)} \prod_{r=1}^{k_1} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{1,1}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^1\right)} \right|^2 \sim \\ &\sim \frac{\sin U}{U},\ L \to \infty, \\ &t \in [\pi L + \mu, \pi L + \mu + U]. \end{aligned} \tag{2.7}$$

Now, if we put (in our present context)

$$\begin{aligned} &\mu = 0, L \to 2L, \\ &\alpha_r^{2,2} \to \alpha_r^{3,k_3},\ r = 0, 1, \dots, k_3, \\ &\beta_r^2 \to \beta_r^{k_3},\ r = 1, \dots, k_3, \\ &\alpha_r^{1,1} \to \alpha_r^{4,k_4},\ r = 0, 1, \dots, k_4, \\ &\beta_r^1 \to \beta_r^{k_4},\ r = 1, \dots, k_4, \end{aligned}$$

then we obtain from (2.7) in the case

$$t \in [2\pi L, 2\pi L + U],\ U \in \left(0, \frac{\pi}{2} - \epsilon\right]$$

the following

Lemma 3.

$$\begin{aligned} &\frac{\cos^2(\alpha_0^{3,k_3})}{\cos U} \prod_{r=1}^{k_3} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{3,k_3}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^{k_3}\right)} \right|^2 - \\ &- \frac{\sin^2(\alpha_0^{4,k_4})}{\cos U} \prod_{r=1}^{k_4} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{4,k_4}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^{k_4}\right)} \right|^2 \sim \frac{\sin U}{U},\ L \to \infty, \end{aligned} \tag{2.8}$$

where

$$
\begin{aligned}
&f_3(t) = \cos^2 t \to \prod_{r=1}^{k_3} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{3,k_3}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^{k_3}\right)} \right|^2 , \\
&f_4(t) = \sin^2 t \to \prod_{r=1}^{k_4} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{4,k_4}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^{k_4}\right)} \right|^2 , \\
&t \in [2\pi L, 2\pi L + U],
\end{aligned} \tag{2.9}
$$

and

$$
\begin{aligned}
&\alpha_0^{3,k_3} = \alpha_0^{2,2}(U, 0, 2L, k_3; f_3), \dots \\
&\beta_r^{k_3} = \beta_r^2(U, 0, 2L, k_3), \\
&\alpha_0^{4,k_4} = \alpha_0^{1,1}(U, 0, 2L, k_4; f_4), \dots \\
&\beta_r^1 \to \beta_r^{k_4}, \ r = 1, \dots, k_4, \\
&\beta_r^{k_4} = \beta_r^1(U, 0, 2L, k_4).
\end{aligned}
$$

3. THEOREM

3.1. Now, we obtain by making use of (2.2), (2.5) and (2.7) the following nonlinear interaction formula.

Theorem.

$$
\begin{aligned}
&\prod_{r=1}^{k_1} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{1,k_1}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^{k_1}\right)} \right|^2 \sim \\
&\sim \frac{\cos(\alpha_0^{2,k_2})}{\cos^3(\alpha_0^{1,k_1})} \prod_{r=1}^{k_2} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{2,k_2}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^{k_2}\right)} \right|^2 - \frac{U^2}{3} \frac{1}{\cos^2(\alpha_0^{1,k_1}) \cos^3 U} \times \\
&\times \left\{ \cos^2(\alpha_0^{3,k_3}) \prod_{r=1}^{k_3} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{3,k_3}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^{k_3}\right)} \right|^2 - \sin^2(\alpha_0^{4,k_4}) \prod_{r=1}^{k_4} \left| \frac{\zeta\left(\frac{1}{2} + i\alpha_r^{4,k_4}\right)}{\zeta\left(\frac{1}{2} + i\beta_r^{k_4}\right)} \right|^2 \right\}^3 , \\
&L \to \infty, \\
&1 \le k_1, k_2, k_3, k_3 \le k_0.
\end{aligned} \tag{3.1}
$$

Next, we give following corollaries from the Theorem, (comp. (b) in the beginning of the section 1.3).

Corollary 1.

$$\prod_{r=1}^{k_2}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{2,k_2}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_2}\right)}\right|^2 \sim$$

$$\sim \frac{\cos^3(\alpha_0^{1,k_1})}{\cos(\alpha_0^{2,k_2})}\prod_{r=1}^{k_1}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{1,k_1}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_1}\right)}\right|^2+\frac{U^2}{3}\frac{1}{\cos(\alpha_0^{2,k_2})\cos^3 U}\times \tag{3.2}$$

$$\times\left\{\cos^2(\alpha_0^{3,k_3})\prod_{r=1}^{k_3}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{3,k_3}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_3}\right)}\right|^2-\sin^2(\alpha_0^{4,k_4})\prod_{r=1}^{k_4}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{4,k_4}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_4}\right)}\right|^2\right\}^3,$$

$L\to\infty$.

Corollary 2.

$$\prod_{r=1}^{k_3}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{3,k_3}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_3}\right)}\right|^2 \sim$$

$$\sim \frac{\sin^2(\alpha_0^{4,k_4})}{\cos^2(\alpha_0^{3,k_3})}\prod_{r=1}^{k_4}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{4,k_4}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_4}\right)}\right|^2+$$

$$+\left\{\frac{3}{U^2}\frac{\cos^3 U\cos(\alpha_0^{2,k_2})}{\cos^6(\alpha_0^{3,k_3})}\prod_{r=1}^{k_2}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{2,k_2}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_2}\right)}\right|^2-\right. \tag{3.3}$$

$$\left.-\frac{3}{U^2}\frac{\cos^3 U\cos^3(\alpha_0^{1,k_1})}{\cos^6(\alpha_0^{3,k_3})}\prod_{r=1}^{k_1}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{1,k_1}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_1}\right)}\right|^2\right\}^{1/3},$$

$L\to\infty$.

Corollary 3.

$$\prod_{r=1}^{k_4}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{4,k_4}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_4}\right)}\right|^2 \sim$$

$$\sim \frac{\cos^2(\alpha_0^{3,k_3})}{\sin^2(\alpha_0^{4,k_4})}\prod_{r=1}^{k_3}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{3,k_3}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_3}\right)}\right|^2-$$

$$-\left\{\frac{3}{U^2}\frac{\cos^3 U\cos(\alpha_0^{2,k_2})}{\sin^6(\alpha_0^{4,k_4})}\prod_{r=1}^{k_2}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{2,k_2}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_2}\right)}\right|^2-\right. \tag{3.4}$$

$$\left.-\frac{3}{U^2}\frac{\cos^3 U\cos^3(\alpha_0^{1,k_1})}{\sin^6(\alpha_0^{4,k_4})}\prod_{r=1}^{k_1}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{1,k_1}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_1}\right)}\right|^2\right\}^{1/3},$$

$L\to\infty$.

3.2. Let us remind the following correspondences (see (2.1), (2.2); (2.3), (2.4); (2.9)):

$$
\begin{aligned}
&f_1(t)=\cos^3 t \to \prod_{r=1}^{k_1}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{1,k_1}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_1}\right)}\right|^2=(k_1,f_1),\\
&f_2(t)=\cos t \to \prod_{r=1}^{k_2}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{2,k_2}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_2}\right)}\right|^2=(k_2,f_2),\\
&f_3(t)=\cos^2 t \to \prod_{r=1}^{k_3}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{3,k_3}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_3}\right)}\right|^2=(k_3,f_3),\\
&f_4(t)=\sin^2 t \to \prod_{r=1}^{k_4}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{4,k_4}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_4}\right)}\right|^2=(k_4,f_4),\\
&1\le k_1,k_2,k_3,k_4\le k_0.
\end{aligned}
\tag{3.5}
$$

Remark 5. First, we see that the formulae (3.1) – (3.4) define the set of nonlinear interactions of the $(k_0)^4$ oscillating systems in (3.5). Namely, this set contains $4(k_0)^4$ elements of different type. Now, if we use our short notions in (3.5) we may write down the following diagram



4. SHORT FUNCTIONAL ALGEBRA

We shall call each of the following type of functional combinations

$$
\cos^2(\alpha_0^{3,k_3})\prod_1^{k_3}-\sin^2(\alpha_0^{4,k_4})\prod_1^{k_4}, \tag{4.1}
$$

$$
\frac{3}{U^2}\cos^3 U\cos(\alpha_0^{2,k_2})\prod_1^{k_2}-\frac{3}{U^2}\cos^3 U\cos^3(\alpha_0^{1,k_1})\prod_1^{k_1} \tag{4.2}
$$

of two ζ-oscillating systems as the two-parts form. Since

$$
1\le k_1,k_2,k_3,k_4\le k_0
$$

then the set of formulae (4.1) (just as similar set (4.2)) contains

$$
(k_0)^2
$$

two-part forms of different type. In this direction we have (see (3.1)) the following

Corollary 4.

$$\begin{aligned}
&\left\{\cos^2(\alpha_0^{3,k_3})\prod_{r=1}^{k_3}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{3,k_3}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_3}\right)}\right|^2 -\right.\\
&\left.-\sin^2(\alpha_0^{4,k_4})\prod_{r=1}^{k_4}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{4,k_4}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_4}\right)}\right|^2\right\}^3 \sim\\
&\sim \frac{3}{U^2}\cos^3 U\cos(\alpha_0^{2,k_2})\prod_{r=1}^{k_2}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{2,k_2}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_2}\right)}\right|^2 -\\
&-\frac{3}{U^2}\cos^3 U\cos^3(\alpha_0^{1,k_1})\prod_{r=1}^{k_1}\left|\frac{\zeta\left(\frac{1}{2}+i\alpha_r^{1,k_1}\right)}{\zeta\left(\frac{1}{2}+i\beta_r^{k_1}\right)}\right|^2,\\
&L\to\infty.
\end{aligned} \tag{4.3}$$

Remark 6. The following property is expressed by the formula (4.3): the cube of two-parts form (4.1) is asymptotically equal to the two-part form (4.2). Of course, we have also the following formula

$$\sqrt[3]{(4.2)} \sim (4.1).$$

Next, it is true (see (4.3)) that for every fixed pair (k_3, k_4) we have set of $(k_0)^2$ asymptotic formulae of different types for the cube of corresponding two-parts form (4.1). For example, in the case $k_0 = 10^3$ we have 10^6 of these formulae.

Remark 7. Consequently, we may regard the formula (4.3) as a kind of simplification of the well-known school-formula

$$(a-b)^3 = a^3 - 3a^2b + 2ab^2 - b^3 \tag{4.4}$$

in this short functional algebra generated by the formula (3.1). Namely, the right-hand side of (4.3) contains two-parts form (i.e. the two members only in comparison with (4.4)).

5. The iteration formula as a constraint on the corresponding vector-valued functions generated by the operator $\hat{H}$

Let us remind that we have defined (see [8], Definition 2 and Definition 5; [9], Definition) new type of vector-valued operator $\hat{H}$ as follows:

$$\begin{aligned}
&\forall f(t)\in\tilde{C}_0[T,T+U]\to\hat{H}f(t) =\\
&=(\alpha_0,\alpha_1,\dots,\alpha_k,\beta_1,\dots,\beta_k),\ k=1,\dots,k_0,
\end{aligned}$$

for every fixed k.

Consequently, we have the following set of k_0 vector-valued functions

$$(\alpha_0,\alpha_1,\dots,\alpha_k,\beta_1,\dots,\beta_k),\ k=1,\dots,k_0. \tag{5.1}$$

Remark 8. That is, we may say that we have defined the following matrix-valued operator $\hat{H}$:

$$f(t) \overset{\hat{H}}{\to} \begin{pmatrix} \alpha_0 & \alpha_1 & \beta_1 & 0 & \dots & & & & & \\ \alpha_0 & \alpha_1 & \alpha_2 & \beta_1 & \beta_2 & 0 & \dots & & & \\ \alpha_0 & \alpha_1 & \alpha_2 & \alpha_3 & \beta_1 & \beta_2 & \beta_3 & 0 & \dots & \\ \vdots & & & & & & & & & \\ \alpha_0 & \alpha_1 & \alpha_2 & \alpha_3 & \dots & \alpha_{k_0} & \beta_1 & \beta_2 & \dots & \beta_{k_0} \end{pmatrix}_{k_0\times(2k_0+1)} .$$

Next, it is true that every interaction formula:

(a) contains some set of ζ-oscillating systems,

(b) every ζ-oscillating system from that set contains the components of corresponding vector-valued function of type (5.1).

Remark 9. Consequently, we may understand every interaction formula (3.1), for example, as the constraint on the set of corresponding vector-valued functions of type (5.1) which are contained in this formula.

References

[1] J. Moser, 'Jacob's ladders and almost exact asymptotic representation of the Hardy-Littlewood integral', Math. Notes 88, (2010), 414-422, arXiv: 0901.3937.

[2] J. Moser, 'Jacob's ladders, structure of the Hardy-Littlewood integral and some new class of nonlinear integral equations', Proc. Steklov Inst. 276 (2011), 208-221, arXiv: 1103.0359.

[3] J. Moser, 'Jacob's ladders, reverse iterations and new infinite set of L_2-orthogonal systems generated by the Riemann zeta-function, arXiv: 1402.2098.

[4] J. Moser, 'Jacob's ladders, ζ-factorization and infinite set of metamorphoses of a multiform', arXiv: 1501.07705v2.

[5] J. Moser, 'Jacob's ladders, Riemann's oscillators, quotient of the oscillating multiforms and set of metamorphoses of this system', arXiv: 1506.00442.

[6] J. Moser, 'Jacob's ladders, factorization and metamorphoses as an appendix to the Riemann functional equation for $\zeta(s)$ on the critical line', arXiv: 1506.00442v1.

[7] J. Moser, 'Jacob's ladders, $\mathcal{Z}_{\zeta,Q^2}$-transformation of real elementary functions and telegraphic signals generated by the power functions', arXiv: 1602.04994.

[8] J. Moser, 'Jacob's ladders, interactions between ζ-oscillating systems and ζ-analogue of an elementary trigonometric identity', arXiv: 1609.09293v1.

[9] J. Mosser, 'Jacob's ladders and some unbounded decomposition of the ζ-oscillating systems on products of other ζ-oscillating systems as an ζ-analogue of the prime decomposition', arXiv:1701.08979v1.

Department of Mathematical Analysis and Numerical Mathematics, Comenius University, Mlynska Dolina M105, 842 48 Bratislava, SLOVAKIA

E-mail address: jan.mozer@fmph.uniba.sk